Branches Chandelier by Brothers Dressler

Installation Manual page 1

Models
Without Crystals: BR800E-05 BR1200E-05 BR1650E-05 BR1850E-05
With Crystals: BRC800E-05 BRC1200E-05 BRC1650E-05 BRC1850E-05

Note: Sizes and number of bulbs vary depending on Model.

Warning!
To ensure the safety of this fixture please follow these instructions completely both during installation and use. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
MAX 25W TYPE E12 per socket
Dry locations only

Technical Specs.
25 W incandescent bulbs 120V E12 Socket
Hanging up to 1800mm (72") standard or custom length available

CONTENTS
1- STEM FIXTURE - INCLUDES LIGHT FIXTURE AND CABLE SYSTEM
AS SHOWN ON LEFT. WITH CANOPY AND GEM BAR.
2- 8-32 1-1/4" SCREWS QTY 2 TO AFFIX GEM BAR TO CABLE BOX
3- WIRE CONNECTORS QTY 2
4- BRANCHES WITH CRYSTALS ATTACHED QTY 7
5- 5/16-18 1" BUTTON HEAD BOLTS QTY 7
6- 3/16" ALLEN WRENCH QTY 1
7- 25 WATT LIGHT BULB QTY 6

STEP 2

Step 1
Empty carton and ensure that all of the contents are there.

Step 2
Hang stem fixture portion of light using #8-32 machine screws, (provided), to attach gem bar to cable box.

Step 3
If change is necessary set drop height by adjusting cable length to position by loosening cable gripper.

Set feed wire length and trim excess.
Place knot above strain relief.

Step 4
Connect coaxial connections. Affix ground wire. Close canopy using barrel coupler.

Adjust cable cord holders to desired positions to support the cord.

STEP 3

STEP 4

BROTHERS DRESSLER

© 2012 Brothers Dressler Inc. All rights reserved.

Branches Chandelier by Brothers Dressler

Installation Manual page 2

Step 5
Affix branches to fixture with 5/16 NF bolt using allen key provided. Alternate sides to ease installation or have someone steady the fixture.

Step 6
Adjust branches for appearance, balance and bulb room using allen wrench provided.

Step 7
Screw light bulbs, provided, in sockets.
For information on replacement bulbs contact info@brothersdressler.com

Turn fixture on.

Care: Use damp cloth to dust. Periodically wipe with beeswax as desired.

For additional assistance please contact info@brothersdressler.com

Approved to UL and CSA standards by Intertek ETL

STEP 6

NOTE CRYSTAL VERSION SHOWN

BROTHERS DRESSLER

© 2012 Brothers Dressler Inc. All rights reserved.