Branches Chandelier by Brothers Dressler

Installation Manual page 1

Models
Without Crystals: BR800E-05 BR1200E-05

Warning!
To ensure the safety of this fixture please follow these instructions completely both during installation and use. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
MAX 25W TYPE E12 per socket
Dry locations only

Technical Specs.
25 W incandescent bulbs 120V E12 Socket
Hanging up to 1800mm (72") standard or custom length available

CONTENTS
1- STEM FIXTURE - INCLUDES LIGHT FIXTURE AND CABLE SYSTEM
AS SHOWN ON LEFT. WITH CANOPY AND GEM BAR.
2- 8-32 1-1/4" SCREWS QTY 2 TO AFFIX GEM BAR TO CABLE BOX
3- WIRE CONNECTORS QTY 2
4- BRANCHES WITH CRYSTALS ATTACHED QTY 7
5- 5/16-18 1" BUTTON HEAD BOLTS QTY 7
6- 3/16" ALLEN WRENCH QTY 1
7- 25 WATT LIGHT BULB QTY 6

STEP 2

Step 1
Empty carton and ensure that all of the contents are there.

Step 2
Hang stem fixture portion of light using #8-32 machine screws, (provided), to attach gem bar to cable box.

Step 3
If change is necessary set drop height by adjusting cable length to position by loosening cable gripper.

Set feed wire length and trim excess.
Place knot above strain relief.

Step 4
Connect coaxial connections. Affix ground wire. Close canopy using barrel coupler.

Adjust cable cord holders to desired positions to support the cord.

STEP 3

STEP 4

BROTHERS DRESSLER

© 2012 Brothers Dressler Inc. All rights reserved.

Branches Chandelier by Brothers Dressler

Installation Manual page 2

Step 5
Affix branches to fixture with 5/16 NF bolt using allen key provided. Alternate sides to ease installation or have someone steady the fixture.

Step 6
Adjust branches for appearance, balance and bulb room using allen wrench provided.

Step 7
Screw light bulbs, provided, in sockets.
For information on replacement bulbs contact info@brothersdressler.com

Turn fixture on.

Your branches pendent light is model

Care: Use damp cloth to dust. Periodically wipe with beeswax as desired.

For additional assistance please contact info@brothersdressler.com

Approved to UL and CSA standards by Intertek ETL

STEP 6

BROTHERS DRESSLER

© 2012 Brothers Dressler Inc. All rights reserved.