




# LEE BROOM



## DECANTER CHANDELIER

### CONTENTS



1X  
ALLEN  
KEY




12 X  
CEILING  
SCREWS



3 X  
PLATE  
SCREWS



5 X  
PENDANT  
FITTING




2 X  
SQUARE  
DECANTER




2 X  
BELL  
DECANTER



1 X  
TULIP  
DECANTER



1X  
CHANDELIER  
BASE PLATE



1X  
CHANDELIER  
TOP PLATE

### ATTENTION

- THE DECANTER CHANDELIER MUST BE INSTALLED BY A PROFESSIONAL, QUALIFIED ELECTRICIAN.
- MINIMUM OF TWO PEOPLE REQUIRED FOR INSTALLATION.
- ENSURE POWER SUPPLY IS DISCONNECTED PRIOR TO INSTALLATION.
- THIS PRODUCT IS FOR INTERIOR USE ONLY AND SHOULD BE INSTALLED IN A DRY ENVIRONMENT.
- PLEASE USE A TRAILING EDGE DIMMER SWITCH WHICH IS SUITABLE FOR THE WATTAGE OUTPUT.
- WHEN SWITCHED ON THE CRYSTAL MAY BECOME HOT.
- CAUTION HEAVY PRODUCT APPROX. WEIGHT 10KG.
- BULBS ARE NOT SUPPLIED.



200W TOTAL  
MAXIMUM  
WATTAGE  
(5 X 40W)

THIS  
PRODUCT  
MUST BE  
EARTHED

110/130V  
50-60 HZ

E26  
LAMP  
HOLDER

### CARE AND CLEANING

- ONLY ATTEMPT TO CLEAN WHEN THE DECANTER CHANDELIER IS SWITCHED OFF
- PLEASE ALLOW A SUITABLE COOLING PERIOD BEFORE ATTEMPTING TO CLEAN THE DECANTER CHANDELIER OR REPLACING THE LIGHT BULB.
- ONLY USE A NON-ABRASIVE, SOFT, DRY, CLOTH WHEN CLEANING THE CRYSTAL.

## ASSEMBLY - MUST BE INSTALLED BY A PROFESSIONAL, QUALIFIED ELECTRICIAN

1. UNSCREW THE X3 SCREWS FROM THE SIDE OF THE CEILING PLATE USING THE PROVIDED ALLEN KEY.
2. SEPARATE THE CHANDELIER BASE PLATE FROM THE TOP PLATE.
3. TERMINATE CONNECTION WIRES AT SUITABLE JUNCTION BOX OR BESA BOX.
4. FEED MAINS WIRE THROUGH THE CENTRAL HOLE OF THE TOP PLATE.
5. FIT TOP PLATE TO CEILING. IT IS RECOMMENDED THAT THE PLATE IS FITTED DIRECTLY INTO A CEILING JOIST. DIFFERENT CEILINGS REQUIRE DIFFERENT TYPES OF FITTINGS ALWAYS CHOOSE SCREWS AND RAW PLUGS THAT ARE APPROPRIATE FOR THE SURFACE MATERIAL.
6. LIFT COVER OFF JUNCTION BOX IN BOTTOM PLATE TO REVEAL CONNECTOR BLOCK.
7. LIFT THE BOTTOM PLATE WITH THE DECANTER SHADES ATTACHED TO THE TOP PLATE. (THIS REQUIRES X2 PEOPLE)
8. CONNECT THE TERMINATED MAINS WIRES TO THE CHANDELIERS JUNCTION BOX. ONCE ALL WIRES ARE CONNECTED FIT COVER BACK ONTO JUNCTION BOX.
9. ALIGN THE SCREW HOLES ON THE SIDE OF THE BOTTOM PLATE WITH THE SIDE HOLES ON THE TOP PLATE. ONCE IN POSITION USE ALLEN KEY SCREWS TO FIX.
10. FIT AN E27 CLEAR GOLF BALL LIGHT BULB IN LAMP HOLDER (40W MAX) TO EACH DECANTER SHADE. (THIS REQUIRES TWO PEOPLE).
11. TO CHANGE THE LIGHT BULBS ENSURE THE POWER TO THE DECANTER CHANDELIER IS SWITCHED OFF. SLIDE THE DECANTER SHADE UP THE WIRE TO ACCESS THE LAMP HOLDER. (THIS REQUIRES TWO PEOPLE).

